

No. TM-PS5-0123E-02

Issued Date: August 3, 2021

Sony Interactive Entertainment Inc.

CS Dept.

Tel:+81(50)-3807-9360

Fax:+81(50)-3807-9595



SIE Inc.

Technical Memo

Approved by	Checked by	Drawn by
<div>SIE CS '21.08.04 Monden</div>		<div>SIE CS '21.08.03 Tone</div>

Subject. Compatibility table for repaired MCB

Description. Some of repaired MCBs cannot be used as a repair part for some models.
The usable combinations of board ID and models are shown below.

A-chassis Standard model:

leading 5 digits of board ID	UCS (K / F) * J1 (K / F) * EU8 / AU3 RU3 BR2 / E32	UCS (G) ** J1 (G) **	CN9
40001	✓		
40002	✓		
179SC	✓		
40003	✓	✓	
40004	✓	✓	
AA001	✓	✓	
AA002	✓	✓	
AA003	✓	✓	
AA004	✓	✓	
AA005	✓	✓	
AA006	✓	✓	
40005	✓		
40006	✓		
40014			✓
40015			✓
40016			✓
40017			✓
40018			✓
40019			✓

* UCS (K / F), J1 (K / F) : made by SKZ or FOX

** UCS (G), J1 (G) : made by GTK

Target model CFI-1000 series / CFI-1100 series

CONFIDENTIAL AND PRIVILEGED

A-chassis Digital edition:

leading 5 digits of board ID	UCS / J1 EU8 / AU3 RU3 BR2 / E32	CN9
40007	✓	
40008	✓	
179ZC	✓	
40009	✓	
40010	✓	
40011	✓	
40012	✓	
40020		✓
40021		✓
40022		✓
40023		✓
40024		✓
40025		✓

B-chassis Standard model:

leading 5 digits of board ID	UCS / J1 EU8 / AU3	RU3 BR2 / E32	CN9
17ARC	✓	✓	
40026	✓	✓	
40027	✓	✓	
AB001	✓	✓	
AB002	✓	✓	
AB003	✓	✓	
AB004	✓	✓	
AB005	✓	✓	
AB006	✓	✓	
40028	✓		
40029	✓		
AB007	✓		
AB008	✓		
AB009	✓		
AB010	✓		
AB011	✓		
AB012	✓		

B-chassis Digital edition:

leading 5 digits of board ID	UCS / J1 EU8 /AU3	RU3 BR2 / E32	CN9
1BS25	✓	✓	
40030	✓	✓	
40031	✓	✓	
AB013	✓	✓	
AB014	✓	✓	
AB015	✓	✓	
AB016	✓	✓	
AB017	✓	✓	
AB018	✓	✓	
40032	✓		
40033	✓		
AB019	✓		
AB020	✓		
AB021	✓		
AB022	✓		
AB023	✓		
AB024	✓		